

# Selection guide UL Circuit Breakers

Emax  
Power breakers



1SDC200010R0201



1SDC200010R0201



1SDC200011R0201

E3					E4					E6					
N-A	S-A	H-A	V-A	X-A	S-A	H-A	V-A	L-A	H-A/f <sup>(1)</sup>	H-A	V-A	L-A	X-A	H-A/f <sup>(1)</sup>	X-A/f <sup>(1)</sup>
2000	800	800	800	800	3200	3200	3200	3200	3200	4000	4000	4000	4000	4000	4000
2500	1200	1200	1200	1200	3600	3600	3600	3600	3600	5000	5000	5000	5000	5000	5000
	1600	1600	1600	1600											
	2000	2000	2000	2000											
	2500	2500	2500												
	3200	3200	3200												
100	100	100	100	100	50	50	50	50	100	50	50	50	50	100	100
65	85	85	125	200	85	100	100	125	100	125	125	150	200	125	200
50	65	85	125	200	65	85	100	125	85	85	125	150	200	85	200
50	65	85	100	14	65	85	100	100	85	85	100	100	100	85	100
50	65	65	85	14	65	85	100	100	85	100	100	100	100	100	100
■	■	■	■	■	■	■	■	■	■	■	■	■	■	■	■
■	■	■	■	■	■	■	■	■	■	■	■	■	■	■	■
■	■	■	■	■	■	■	■	■	■	■	■	■	■	■	■
80	80	80	80	80	80	80	80	80	80	80	80	80	80	80	80
70	70	70	70	70	70	70	70	70	70	70	70	70	70	70	70
30	30	30	30	30	30	30	30	30	30	30	30	30	30	30	30
	404/530					566/656		746			782/908			1034	
	15.91/20.82					22.28/25.83		29.37			30.79/35.78			40.71	
	432/558					594/684		774			810/936			1062	
	17.01/21.97					23.39/26.93		30.47			31.89/36.85			41.81	
	66/80		70/84			97/117		125			140/160			185	
	145/176		154/185			214/258		276			308/353			408	
	104/125		106/128			147/165		200			210/240			275	
	229/275		233/282			324/363		441			463/529			607	

E3 N-A/S-A/H-A/V-A					E4 S-A/H-A/V-A/L-A/H-A/f				E6 H-A/V-A/L-A/X-A/H-A/f/X-A/f	
1200	1600	2000	2500	3200	3200	3600		4000	5000	
15 <sup>(2)</sup>	15 <sup>(2)</sup>	15 <sup>(2)</sup>	15	15	8	8		8	8	
30	30	30	30	30	30	30		30	30	
10 <sup>(3)</sup>	10 <sup>(3)</sup>	8 <sup>(3)</sup>	8	8	5	5		5	3	
30	30	30	30	30	30	30		30	30	