

## Non-automatic switches UL



The switches share the same frames and accessories as the circuit breakers, with the only difference the absence of the trip unit.

The switch is available in both three-pole and four-pole fixed and draw out version and is identified by the code "/MS" (on the label). The electrical characteristics of the switches are given in the following table.

		<b>E1B-A/MS</b>	<b>E1N-A/MS</b>	<b>E2B-A/MS</b>	<b>E2 N-A/MS</b>	<b>E2S-A/MS</b>	<b>E3N-A/MS</b>	<b>E3S-A/MS</b>
Frame size	[A]	800	800	1600	800	800	2000	800
	[A]	1200	1200	—	1200	1200	2500	1200
	[A]	—	—	—	1600	1600	—	1600
	[A]	—	—	—	—	—	—	2000
	[A]	—	—	—	—	—	—	2500
	[A]	—	—	—	—	—	—	3200
Number of Poles		3/4	3/4	3/4	3/4	3/4	3/4	3/4
Capacity of neutral pole for four-pole circuit breakers	[%I <sub>n</sub> ]	100	100	100	100	100	100	100
Rated voltage	[V]	600	600	600	600	600	600	600
Rated maximum voltage	[V]	635	635	635	635	635	635	635
Test voltage (1 min. 50/60 Hz)	[kV]	2.2	2.2	2.2	2.2	2.2	2.2	2.2
Frequency	[Hz]	50-60	50-60	50-60	50-60	50-60	50-60	50-60
Rated short time current	[kA]	42	50	42	50	65	650	650
Version		F-W	F-W	F-W	F-W	F-W	F-W	F-W