

Circuit breaker type ① Non-reversing, three phase



3

UL Listed 12 (Metal dustight)		UL Listed 4 (Watertight)		UL Listed 4X (Stainless steel)		UL Listed 1, 3R, 4, 4X & 12 (Plastic)		UL Listed 7 & 9 non-reversing (Explosion proof)	
Catalog number	List price	Catalog number	List price	Catalog number	List price	Catalog number	List price	Catalog number	List price
A9SM2-84★◆◆	\$ 1110	A9SM4-84★◆◆	\$ 1260	A9SMX-84★◆◆	\$ 1835	A9SMP-84★◆◆	\$ 1050	A9SM7-84★◆◆	\$ 2660
A12SM2-84★◆◆	1140	A12SM4-84★◆◆	1290	A12SMX-84★◆◆	1865	A12SMP-84★◆◆	1080	A12SM7-84★◆◆	2850
A16SM2-84★◆◆	1170	A16SM4-84★◆◆	1320	A16SMX-84★◆◆	1895	A16SMP-84★◆◆	1110	A16SM7-84★◆◆	3030
A26SM2-84★◆◆	1253	A26SM4-84★◆◆	1410	A26SMX-84★◆◆	2000	A26SMP-84★◆◆	1193	A26SM7-84★◆◆	3105
A30SM2-84★◆◆	1335	A30SM4-84★◆◆	1500	A30SMX-84★◆◆	2330	A30SMP-84★◆◆	1275	A30SM7-84★◆◆	3480
A40SM2-84★◆◆	1440	A40SM4-84★◆◆	1635	A40SMX-84★◆◆	2720	A40SMP-84★◆◆	1380	A40SM7-84★◆◆	3860
A50SM2-84★◆◆	1935	A50SM4-84★◆◆	2115	A50SMX-84★◆◆	3275	A50SMP-84★◆◆	1875	A50SM7-84★◆◆	4150
A63SM2-84★◆◆	2160	A63SM4-84★◆◆	2438	A63SMX-84★◆◆	3635	A63SMP-84★◆◆	2100	A63SM7-84★◆◆	5540
A75SM2-84★◆◆	2880	A75SM4-84★◆◆	3225	A75SMX-84★◆◆	4055	A75SMP-84★◆◆	2520	A75SM7-84★◆◆	6850
A95SM2-84★◆◆	3125	A95SM4-84★◆◆	3800	A95SMX-84★◆◆	5200	A95SMP-84★◆◆	3250	A95SM7-84★◆◆	7940
A110SM2-84★◆◆	3870	A110SM4-84★◆◆	4200	A110SMX-84★◆◆	6050	A110SMP-84★◆◆	3700	A110SM7-84★◆◆	11,370
A145SM2-84★◆◆	5235	A145SM4-84★◆◆	5588	A145SMX-84★◆◆	7650	A145SMP-84★◆◆	5400	A145SM7-84★◆◆	13,595
A185SM2-84★◆◆	5610	A185SM4-84★◆◆	6300	A185SMX-84★◆◆	9150	A185SMP-84★◆◆	6150	A185SM7-84★◆◆	14,475
A210SM2-84★◆◆	9045	A210SM4-84★◆◆	9713	A210SMX-84★◆◆	12,510	A210SMP-84★◆◆	9500	A210SM7-84★◆◆	17,775
A260SM2-84★◆◆	10,155	A260SM4-84★◆◆	10,950	A260SMX-84★◆◆	17,250	A260SMP-84★◆◆	10,650	—	—
A300SM2-84★◆◆	10,650	A300SM4-84★◆◆	12,000	A300SMX-84★◆◆	22,800	A300SMP-84★◆◆	11,500	—	—
A400SM2-70★◆◆	12,990	A400SM4-70★◆◆	13,800	A400SMX-70★◆◆	26,850	—	—	—	—
A460SM2-70★◆◆	21,150	A460SM4-70★◆◆	22,500	A460SMX-70★◆◆	28,995	—	—	—	—
A580SM2-70★◆◆	24,450	A580SM4-70★◆◆	26,850	A580SMX-70★◆◆	36,000	—	—	—	—
A750SM2-70★◆◆	27,330	A750SM4-70★◆◆	30,000	A750SMX-70★◆◆	37,650	—	—	—	—

★ Overload relay suffix code. Select from the overload relay selection chart on page 3.6. Overload relays are required for all combination starters. If overload relay is provided by customer, substitute an "X" in place of the ★ and then subtract list price of overload relay from combination starter's list price.

◆ MCP or breaker rating. See MCP codes on page 3.50.

Motor circuit protector data

Motor full load amperes	MCP continuous rating	Suffix code ◆	Catalog number	Starter size	1.5X	2X	4X	5X	6X	7X	8X	9X	10X	11X	12X
.92 – 2.76	3	A	S3L003MW	0	—	—	12	15	18	21	24	27	30	33	36
1.53 – 4.61	5	B	S3L005MW	0	—	—	20	25	30	35	40	45	50	55	60
3.07 – 9.23	10	C	S3L010MW	0	—	—	40	50	60	70	80	90	100	110	120
7.69 – 23.08	25	D	S3L025MW	1	—	—	100	125	150	175	200	225	250	275	300
15.38 – 46.15	50	E	S3L050MW	2	—	—	200	250	300	350	400	450	500	550	600
30.77 – 92.31	100	F	S3L100MW	3	—	—	400	500	600	700	800	900	1000	1100	1200
46.15 – 138.46	150	G	S3L150MW	4	—	—	600	750	900	1050	1200	1350	1500	1650	1800
28.85 – 230.77	250	H	S4L250MW	4	375	500	1000	—	1500	—	2000	—	2500	—	3000
46.15 – 369.23	400	J	S5L400MW	5	600	800	1600	—	2400	—	3200	—	4000	—	4800
69.23 – 553.85	600	K	S6L600MW	6	900	1200	2400	—	3600	—	4800	—	6000	—	7200
92.31 – 738.46	800	L	S6L800MW	7	1200	1600	3200	—	4800	—	6400	—	8000	—	9600
115.38 – 923.07	1000	M	S7H1000MW	7	1500	2000	4000	—	6000	—	8000	—	10,000	—	12,000
138.46 – 1107.69	1200	N	S7H1200MW	7	1800	2400	4800	—	7200	—	9600	—	12,000	—	14,400