


Approximate dimensions for combination starters

2 Speed, 1 winding, non-fused w/CCT
2 Speed, 1 winding, fused combination w/CCT

Combination starters



3

2 Speed - 1 Winding, non-fused w/CCT

Starter size	Enclosure type	A	B	C
A9 – A40	1	14	12	8
	4	14	12	8
	4X Stainless	14	12	6
	4X Plastic	14	12	7
	12	14	12	8
A50 – A75	1	20	16	8
	3R	20	16	8
	4	20	16	8
	4X Stainless	20	16	8
	4X Plastic	20	16	8
A95 – A110	1	30	30	8
	3R	30	30	10
	4	30	30	10
	4X Stainless	30	30	10
	4X Plastic	30	30	12
A145 – A185 (NF200)	1	36	30	8
	3R	36	30	8
	4	36	30	8
	4X Stainless	36	30	8
	4X Plastic	–	–	–
A210 (NF200)	1	42	36	13
	3R	36	36	12
	4	36	36	12
	4X Stainless	36	36	12
	4X Plastic	–	–	–
A260 – A300 (NF400)	1	42	36	13
	3R	42	36	13
	4	42	36	13
	4X Stainless	42	36	13
	4X Plastic	–	–	–
A400 (NF600)	1	–	–	–
	3R	60	36	12
	4	60	36	12
	4X Stainless	60	36	12
	4X Plastic	–	–	–
A460 (NF600) A580 (NF800) A750 (NF1200)	1	87	36	24
	3R	87	36	24
	4	–	–	–
	4X Stainless	–	–	–
	4X Plastic	87	36	24

2 Speed - 1 Winding, fused combination w/CCT

Starter size	Enclosure type	A	B	C
A9 – A40	1	20	16	8
	3R	20	16	8
	4	20	16	8
	4X Stainless	20	16	8
	4X Plastic	20	16	8
A50 – A75	1	30	24	12
	3R	30	24	8
	4	30	24	8
	4X Stainless	30	24	8
	4X Plastic	30	20	12
A95 – A110	1	30	24	8
	3R	42	30	12
	4	42	30	12
	4X Stainless	42	30	12
	4X Plastic	–	–	–
A145 – A185 (F400)	1	42	30	12
	3R	42	30	12
	4	42	30	12
	4X Stainless	36	36	12
	4X Plastic	–	–	–
A210 (F400)	1	42	36	13
	3R	36	36	12
	4	36	36	12
	4X Stainless	36	36	12
	4X Plastic	–	–	–
A260 – A300 (F600)	1	42	36	13
	3R	42	36	12
	4	42	36	12
	4X Stainless	42	36	12
	4X Plastic	–	–	–
A400 (F800)	1	–	–	–
	3R	60	36	12
	4	60	36	12
	4X Stainless	60	36	12
	4X Plastic	–	–	–
A460 (F800) A580 (NF1200 + fuse block) A750 (NF 1600 + fuse block)	1	87	36	24
	3R	87	36	24
	4	–	–	–
	4X Stainless	–	–	–
	4X Plastic	87	36	24