


Approximate dimensions Autotransformer w/CCT Autotransformer, non-fused combination w/CCT

3



Autotransformer w/CCT

Starter size	Enclosure type	A	B	C
A9 – A40	1	20	16	8
	3R	20	16	8
	4	20	16	8
	4X Stainless	20	16	8
	4X Plastic	20	16	8
12	20	16	8	
A50 – A75	1	24	20	10
	3R	24	20	10
	4	24	20	10
	4X Stainless	24	20	10
	4X Plastic	30	20	12
12	24	20	10	
A95 – A110	1	30	24	12
	3R	30	30	12
	4	30	30	12
	4X Stainless	30	30	12
	4X Plastic	30	30	12
12	30	30	12	
A145 – A260	1	36	30	12
	3R	36	30	12
	4	36	30	12
	4X Stainless	36	30	12
	4X Plastic	–	–	–
12	36	30	12	
A300	1	48	36	17
	3R	48	36	16
	4	–	–	–
	4X Stainless	–	–	–
	4X Plastic	–	–	–
12	48	36	16	
A400 – A750	1	87	36	24
	3R	87	36	24
	4	–	–	–
	4X Stainless	–	–	–
	4X Plastic	–	–	–
12	87	36	24	

Autotransformer, non-fused combination w/CCT

Starter size	Enclosure type	A	B	C
A9 – A40	1	20	16	8
	3R	20	16	8
	4	20	16	8
	4X Stainless	20	16	8
	4X Plastic	20	16	8
12	20	16	8	
A50 – A75	1	30	24	12
	3R	30	24	8
	4	30	24	8
	4X Stainless	30	24	8
	4X Plastic	30	20	12
12	30	24	8	
A95 – A110	1	36	30	12
	3R	36	30	12
	4	36	30	12
	4X Stainless	36	30	12
	4X Plastic	–	–	–
12	36	30	12	
A145 – A260	1	36	30	12
	3R	36	30	12
	4	36	30	12
	4X Stainless	36	30	12
	4X Plastic	–	–	–
12	36	30	12	
A300	1	48	36	17
	3R	48	36	16
	4	48	36	16
	4X Stainless	–	–	–
	4X Plastic	–	–	–
12	48	36	16	
A400 – A750	1	87	36	24
	3R	87	36	24
	4	–	–	–
	4X Stainless	–	–	–
	4X Plastic	–	–	–
12	87	36	24	