


## Approximate dimensions

Wye-delta, open transition, combination, fused

Wye-Delta, open transition, combination, breaker

Reduced voltage  
starters



3

### Wye-Delta, open transition, combination, fused

Starter size	Enclosure type	A	B	C
A9 – A40	1	14	12	8
	3R	14	12	8
	4	14	12	8
	4X Stainless	14	12	6
	4X Plastic	14	12	7
	12	14	12	8
A50 – A75	1	24	16	8
	3R	24	16	8
	4	24	16	8
	4X Stainless	24	16	8
	4X Plastic	24	16	8
	12	24	16	8
A95 – A110	1	36	30	8
	3R	36	30	8
	4	36	30	8
	4X Stainless	36	30	8
	4X Plastic	40	30	12
	12	36	30	8
A145 (F400) A185 (F600)	1	42	36	9
	3R	36	36	8
	4	36	36	8
	4X Stainless	36	36	12
	4X Plastic	–	–	–
	12	36	36	8
A210 (F600) A260 (F800)	1	–	–	–
	3R	60	36	10
	4	60	36	10
	4X Stainless	60	36	10
	4X Plastic	–	–	–
	12	60	36	10
A300 (NF1200+FB) A400 (NF1600+FB) A460 (NF1600+FB) A580 (NF2000+FB) A750 (NF3150+FB)	1	87	36	24
	3R	87	36	24
	4	–	–	–
	4X Stainless	–	–	–
	4X Plastic	–	–	–
	12	87	36	24

### Wye-Delta, open transition, combination, breaker

Starter size	Enclosure type	A	B	C
A9 – A40	1	14	12	8
	3R	14	12	8
	4	14	12	8
	4X Stainless	16	12	6
	4X Plastic	14	12	7
	12	14	12	8
A50 – A75	1	24	20	8
	3R	24	20	8
	4	24	20	8
	4X Stainless	24	20	8
	4X Plastic	30	20	12
	12	24	20	8
A95 – A110	1	36	30	8
	3R	36	30	8
	4	36	30	8
	4X Stainless	36	30	8
	4X Plastic	40	30	12
	12	36	30	8
A145 (S6) A185 (S6)	1	42	36	9
	3R	36	36	8
	4	36	36	8
	4X Stainless	36	36	12
	4X Plastic	–	–	–
	12	36	36	8
A210 (S7) A300 (S7)	1	42	36	13
	3R	36	36	12
	4	36	36	12
	4X Stainless	36	36	12
	4X Plastic	–	–	–
	12	36	36	12
A400 (S8) A750 (S8)	1	87	36	24
	3R	87	36	24
	4	–	–	–
	4X Stainless	–	–	–
	4X Plastic	–	–	–
	12	87	36	24